

Datasheet SENSE-12INI

Parameters

| Electrical Parameters: | |
|-------------------------------|------------------------|
| PieroNet power supply | 12-30V DC |
| Static power consumption | 40mA/24V DC |
| Dynamic power consumption | 90mA/24V DC |
| IR transmit frequency | 38kHz |
| IR emission distance | 4m |
| Illumination detection range | 0-5000Lux |
| PIR sensing range in diameter | 6m (install height-3m) |
| Ultrasonic sensor in diameter | 8m |
| Environmental Conditions: | |
| Working temperature | -5°~45°C |
| Working relative humidity | Up to 90% |

Approved:

Storage temperature

Storage relative humidity

CE, RoHS

| Product Information: | |
|----------------------|----------------------|
| Dimensions | 110(Diameter)×33(mm) |
| Net weight | 206.7(g) |
| Housing material | Lens, ABS |
| Installation | Ceiling mount |
| Protection rating | IP20 |

-20°~+60°C

Up to 93%

Important Notes

- Installation Location If use PIR function indoor, please keep it away from AC outlets and heat source.
- Environment temperature if use PIR function, please make sure the temperature is below 36°C.
- Detect target PIR only can detect moving objects with heat radiation like human, animal, ultrasonic can detect all moving objects.
- PieroNet cable CAT5E or PieroNet cable.
- PieroNet connection Series connection (hand-in-hand)
- Installation Indoor and ceiling-mount, keep it away from AC outlet.

Safety Precautions



will damage the PieroNet interface of this module.

Do not get AC power into PieroNet wire, it will damage

- Avoid contact with liquids or corrosive gases.
- Ensure good ventilation.

Overview



SENSE-12IN1 12 in 1 sensor includes temperature sensor, PIR motion sensor, LUX sensor ,ultrasonic sensor, dry contacts, IR received, IR emitter, 2-channel 5A relay output and logic block.

Functions

- Temperature, LUX, PIR motion, ultrasonic, 2 dry contact inputs, 2 external inputs, logic, total 9 inputs.
- 2-channel 5A Relay output.
- Build PID for constant LUX control.
- Supports upgrade from PieroNet.

PieroNet Cable Guide

| CAT5/CAT5E | PieroNet |
|----------------------------|----------|
| Brown/ Orange | 24V DC |
| Brown white / Orange white | COM |
| Blue white / Green white | DATA- |
| Blue / Green | DATA+ |





all devices in the system.






Dimmensions and Wiring







Package Contents

Detect range

SENSE-12IN1, Datasheet x1